Go to www.vtechphones.com to register your product for enhanced warranty support and latest VTech product news.

DS6250

DECT 6.0 accessory handset for use with VTech models DS6251/DS6251-2/DS6251-3/DS6251-4



You may also view or download the online user's manual for a full set of installation and operation instructions at www.vtechphones.com. In



logo have reduced noise and interference when used with most T-coil equipped hearing aids and cochlear implants. The TIA-1083 Compliant Logo is a trademark of the Telecommunications Industry

# **Congratulations**

on purchasing your new VTech product. Before using this telephone, please read Important safety instructions.

This manual has instructions on how to set up and register your new handset. For instructions on using the handset, see the Abridged user's manual that came with your telephone base.


Canada, visit www.vtechcanada.com.




Telephones identified with this Association. Used under license.

## Parts checklist

Your telephone package contains the following items. Save your sales receipt and original packaging in the event warranty service is necessary.






## Charger overview



1 - Charging pole

## Handset overview



### 1 - Handset earpiece

### 2 - LCD display

## 3 - Softkeys (2)

- Press to select the menu item displayed above the key.
- While in a menu, press to select an item, save an entry or setting, cancel an operation, or back up to the previous menu.

- · During a call, press to hang up a call. • While in a menu, press to cancel an
- operation, back up to the previous menu, or exit the menu display When the handset is ringing, press to mute
- the ringer temporarily.
- Press and hold to erase the missed call indicator while the phone is not in use.

### 5 - ₩ / **A** VOLUME

- Press to show phonebook entries when the telephone is not in use.
- Press to increase the listening volume when on a call, or increase the message playback
- · Press to scroll up while in a menu.
- · While entering names or numbers, press to move the cursor to the right

# To deregister all handsets from the telephone

- Press and hold PAGE on the telephone base and it shows Registering... Please wait for five seconds, then it shows **Deregister all devices?**. Release **PAGE**.
- 2. Quickly press PAGE again or YES. The telephone base shows Deregistered all devices when the registration completes. It takes up to 10 seconds to complete the deregistration process. Before registering the handset again, wait for the cordless handset screen to display To register, see user manual.

## ■ Notes

- If the deregistration process fails, you may need to reset the system and try again. To reset, unplug the power from the telephone base and plug it back in. You cannot deregister the handsets if any other
- system handset is in use. Even if the battery is depleted, you can still deregister the handsets by following the steps. After the handset is charged for at least 10 minutes, the screen shows **To register**, see user manual.

## Operating range

This cordless telephone operates with the maximum power allowed by the Federal Communications Commission (FCC). Even so, this handset and telephone base can communicate over only a certain distance - which can vary with the locations of the telephone base and handse the weather, and the layout of your home or office.

## When the handset is out of range, the handset displays Out of range OR Base no power.

If there is a call while the handset is out of range, it may not ring, or if it does ring, the call may not connect well when you press LINE 1 or LINE 2. Move closer to the telephone base, and then press **LINE 1** or **LINE 2** to answer the call. If the handset moves out of range during a telephone conversation, there may be interference. To improve reception, move closer to the telephone

## \_\_\_\_\_\_

VOLUME ▼ / CID

telephone is not in use

playback volume.

6 - LINE 1 / LINE 2 / FLASH

7 - QUIET#

8 - OPER ()

9 - CALL BLOCK

10 - MUTE/DELETE

characters.

12 - REDIAL/PAUSE

Review the redial list

11 - Microphone

corresponding line.

order of the name

• Press to show the caller ID log when the

· Press to decrease the listening volume

· Press to scroll down while in a menu

Press to make or answer a call on the

move the cursor to the left.

receive a call waiting alert.

during a call, or decrease the message

• While entering names or numbers, press to

· During a call, press to answer an incoming

call on the corresponding line when you

• During message playback, press to call back

the caller if the caller's number is available.

options when reviewing a caller ID log entry.

setting screen, or to deactivate quiet mode.

Press and hold to add a space when entering

Press to block the incoming call when the

During a call, press to mute the microphone.

• When the headset is ringing, press to mute

· While reviewing the redial list, phonebook,

· During message or announce playback,

caller ID log, allow list, block list, or the star

press to delete the playing message or the

• While entering names or numbers, press to

name list, press to delete an individual entry.

telephone is ringing or during the call.

• When the handset is not in use, press to

show the Smart call blocker menu.

the ringer temporarily.

recorded announcement.

delete a digit or character

· While entering names or numbers,

press and hold to delete all digits or

Press repeatedly to show other dialing

• While editing the name of a caller ID log

• Press and hold to enter the quiet mode

entry, press repeatedly to re-arrange the

This power conserving technology reduces power consumption for optimal battery performance. The ECO mode activates automatically whenever the

## General product care

## Taking care of your telephone

Your cordless telephone contains sophisticated electronic parts, so it must be treated with care.

Place the handset down gently. Save the original packing materials to protect your telephone if you ever need to ship it.

Your telephone can be damaged if it gets wet. Do

## **Electrical storms**

Electrical storms can sometimes cause power surges harmful to electronic equipment. For your own safety, take caution when using electrical appliances during storms.

Your telephone has a durable plastic casing that should retain its luster for many years. Clean it only with a dry non-abrasive cloth. Do not use

· Press and hold to insert a dialing pause while dialing or entering numbers into the phonebook

## 13 - PTT / HOLD

- Press to display the PTT menu to begin a PTT
- <u>Press and hold</u> to begin a one-to-group
- broadcast when the handset is not in use. · Press to put a call on hold.
- 14 TONE \*
  - Press to switch to tone dialing temporarily during a call if you have pulse service.
- While entering names, press to change the next letter to upper or lower case.

- 15 🔀 Press and hold to set or dial your voicemail
- · Press repeatedly to add or remove 1 in front of the caller ID log entry before dialing or saving it to the phonebook.

### 16 – Headset jack

Plug in a wired headset for handsfree telephone conversation.

### 17 – ◀测

Make or answer a call using the handset speakerphone via the first available line. • Switch between the handset speakerphone

and the handset earpiece during a call.

## 18 - CHARGE light

 On when the handset is charging in the telephone base or charger.

### Display icons overview

	The battery icon flashes when the battery is low and needs charging.
	The battery icon animates when the battery is charging.
	The battery icon becomes solid when the battery is fully charged.
Ğ	<ul> <li>On when line 1 is in use.</li> <li>On when there is an incoming call on line 1.</li> <li>Flashes when line 1 is on hold.</li> <li>Flashes when you are configuring the Smart call blocker setup for line 1.</li> <li>Indication of a caller ID log entry received from line 1.</li> </ul>

### Flashes when line 2 is on hold. Flashes when you are configuring the Smart call blocker setup for line 2. Indication of a caller ID log entry received from line 2. The handset ringer for line 1 is off. The handset ringer for line 2 is off. The handset ringers for line 1 and line There are new voicemail received on line 1 from your telephone service provider. $\searrow_2$ There are new voicemail received on line 2 from your telephone service provider. There are new voicemail received on line 1 and line 2 from your telephone service provider. $\mathbf{Q}$ There are new answering system message(s) on line 1. Flashes when you have accessed the answering system menu of line 1. There are new answering system message(s) on line 2. Flashes when you have accessed the answering system menu of line 2. There are new answering system ൶ഀ nessage(s) on line 1 and line 2. The answering system of line 1 is 9MS1 turned on Ans OH2 The answering system of line 2 is Ansi ON2 The answering system of line 1 and line 2 is turned on The speakerphone is in use. A wired headset is being used Indication of new missed call. NEW The microphone is muted. MUTE You can perform 3-character alphabetical search to find entries

On when line 2 is in use.

on line 2.


On when there is an incoming call


# Install the battery

Install the battery as shown below.

## ■ Notes

- Use only the battery provided.
- · If the handset will not be used for a long time, disconnect and remove the battery to prevent possible





# Connect and charge the battery

vtech

User's manua

44 JRL 5

pas 7 TUV 8 MYTE 9


OME X SPER O CONET#

PIT FEOW. WITE BLOCK

vtech

- NOTES · Use only the power adapter supplied with this product.
- · Charge the battery provided with or identified for ise with this product only in accordance with the instructions and limitations specified in this manual.

## Connect the charge



# Charge the battery


Place the handset in the charger to charge.



Once you have installed the battery, the handset LCD display indicates the battery status (see the following table).

## Notes

- For best performance, keep the handset in the telephone base or charger when not in use.
- The battery is fully charged after 12 hours of continuous charging.



## Before use

## Add and register a handset

You can add new **DS6250** handsets (purchased separately) to your **DS6251/DS6251-2/DS6251-3/ D\$6251-4** telephone system. Your telephone system supports a maximum of 12 handsets.

Each handset must be registered with the telephone base before use. When first purchased, each expansion handset displays To register, see user manual

# □ Note

· Charge the new handset without interruption for at least 30 minutes before registering it to the

To register a handset to the telephone base: • Place the new handset in the telephone base.



DS6251 base



Do not place the handset in the charger.

After about 10 seconds, the handset displays Registering... Please wait. When the registration process completes, both the handset and the telephone base display **HANDSET X Registered** (HANDSET represents the handset name, X represents the handset number) and both the handset and the telephone base beep.

DS6251 base

- 1. Press and hold PAGE on the telephone base and it shows Registering... Please wait. Release **PAGE**.
- 2. Quickly press QUIET# on the handset. The handset shows Registering... Please wait. When the registration process completes. both the handset and the telephone base display HANDSET X Registered (HANDSET represents the handset name, **X** represents the handset number) and both the handset and the telephone base beep.

If registration fails, the system will automatically try to register again. If registration fails after the third try, **Registration failed** appears on both screens. The handset shows To register, see user manual and the telephone base returns to idle mode. This may take up to five minutes to occur. Please start the registration process again.

## ■ Note

· You cannot register a handset if any other system

## **Deregister handsets**

If you want to replace a handset or reassign the designated handset number of a registered handset, you must deregister all the handsets and then individually register each handset.

If you want to register a handset to another telephone base, you must deregister all handsets, and then register each handset individually to the desired telephone base.

# ECO mode

handset is synchronized with the telephone base.

Avoid rough treatment

## **Avoid water**

not use the handset outdoors in the rain, or handle it with wet hands. Do not install the telephone base near a sink, bathtub or shower

## Cleaning your telephone

dampened cloth or cleaning solvents of any kind.

## mportant safety instructions

When using your telephone equipment, basic safety precautions should always be followed to reduce the risk of fire, electric shock and injury,


- including the following: Read and understand all instructions.
- Follow all warnings and instructions marked on the product. Unplug this product from the wall outlet before cleaning. Do not use liquid or aerosol
- cleaners. Use a damp cloth for cleaning. 4. Do not use this product near water such as near a bath tub, wash bowl, kitchen sink, laundry tub or a swimming pool, or in a wet
- basement or shower Do not place this product on an unstable
- table, shelf, stand or other unstable surfaces. Avoid placing the telephone system in places with extreme temperature, direct sunlight, or other electrical devices. Protect your phone from moisture, dust, corrosive liquids and
- Slots and openings in the back or bottom of the telephone base and handset are provided for ventilation. To protect them from overheating, these openings must not be blocked by placing the product on a soft surface such as a bed, sofa or rug. This product should never be placed near or over a radiator or heat register. This product should not be placed in any area where proper ventilation is not provided.
- 8. This product should be operated only from the type of power source indicated on the marking label. If you are not sure of the type of power supply in your home or office,
- consult your dealer or local power company. 9. Do not allow anything to rest on the power cord. Do not install this product where the cord may be walked on
- 10. Never push objects of any kind into this product through the slots in the telephone base or handset because they may touch dangerous voltage points or create a short circuit. Never spill liquid of any kind on the product.
- 11. To reduce the risk of electric shock, do not disassemble this product, but take it to an authorized service facility. Opening or removing parts of the telephone base or handset other than specified access doors may expose you to dangerous voltages or other


risks. Incorrect reassembling can cause electric shock when the product is subsequently used. 12. Do not overload wall outlets and extension

- 13. Unplug this product from the wall outlet and refer servicing to an authorized service facility
- under the following conditions: • When the power supply cord or plug is
- damaged or frayed. · If liquid has been spilled onto the product. If the product has been exposed to rain or
- · If the product does not operate normally by following the operating instructions. Adjust only those controls that are covered by the operation instructions. Improper adjustment of other controls may result in damage and often requires extensive work by an authorized technician to restore the product
- to normal operation • If the product has been dropped and the telephone base and/or handset has been
- damaged • If the product exhibits a distinct change in performance.
- 14. Avoid using a telephone (other than cordless) during an electrical storm. There is a remote risk of electric shock from lightning.

15. Do not use the telephone to report a gas

- leak in the vicinity of the leak. Under certain circumstances, a spark may be created when the adapter is plugged into the power outlet, or when the handset is replaced in its cradle. This is a common event associated with the closing of any electrical circuit. The user should not plug the phone into a power outlet, and should not put a charged handset into the cradle, if the phone is located in an environment containing concentrations of flammable or flame-supporting gases. unless there is adequate ventilation. A spark in such an environment could create a fire or explosion. Such environments might include: medical use of oxygen without adequate ventilation; industrial gases (cleaning solvents; gasoline vapors; etc.); a leak of natural gas;
- 16. Only put the handset of your telephone next to your ear when it is in normal talk mode.
- 17. The power adapter is intended to be correctly oriented in a vertical or floor mount position. The prongs are not designed to hold the plug in place if it is plugged into a ceiling, underthe-table or cabinet outlet.





- 18. For pluggable equipment, the socket-outlet shall be installed near the equipment and shall
- 19. **CAUTION:** Use only the batteries indicated in this manual. There may be a risk of explosion if a wrong type of battery is used for the handset. Use only the supplied rechargeable batteries or replacement batteries (BT183342) BT283342) for the handset. Do not dispose of batteries in a fire. They may explode.
- 20. Use only the adapter included with this product. Incorrect adapter polarity or voltage can seriously damage the product. Base unit power adapter: Output: 6V DC @ 600mA. Charger unit power adapter: Output: 6V DC @ 400mA.

### **SAVE THESE INSTRUCTIONS**

- Use only the battery provided or equivalent. To order a replacement, visit our website at www.vtechphones.com or call 1 (800) 595-9511. In Canada, go to www.vtechcanada.com or call 1 (800) 267-7377.
- Do not dispose of the battery in a fire. Check with local waste management codes for special disposal instructions.
- Do not open or mutilate the battery. Released electrolyte is corrosive and may cause burns or injury to the eyes or skin. The electrolyte may be toxic if swallowed.
- Exercise care in handling batteries in order not to create a short circuit with conductive
- Charge the battery provided with this product only in accordance with the instructions and limitations specified in this manual

### **Precautions for users of implanted cardiac** pacemakers

Cardiac pacemakers (applies only to digital cordless telephones):

Wireless Technology Research, LLC (WTR), an independent research entity, led a multidisciplinary evaluation of the interference between portable wireless telephones and implanted cardiac pacemakers. Supported by the U.S. Food and Drug Administration, WTR recommends to physicians

## Pacemaker patients

- Should keep wireless telephones at least six inches from the pacemaker.
- Should NOT place wireless telephones directly over the pacemaker, such as in a breast pocket,

when it is turned ON. 9. Ne déposez rien sur le cordon d'alimentation. Should use the wireless telephone at the ear Installez cet appareil dans un endroit sécuritaire, là où personne ne pourra opposite the pacemaker trébucher sur la ligne d'alimentation ni le WTR's evaluation did not identify any risk to bystanders with pacemakers from other persons cordon téléphonique modulaire. using wireless telephones.

10. N'insérez jamais d'objets à travers les fentes et ouvertures de cet appareil, car ils pourraient toucher à des points de tension dangereux ou court-circuiter des pièces, ce qui constituerait un risque d'incendie ou d'électrocution. N'échappez pas de liquides dans l'appareil.

- Afin de réduire les risques d'incendie, de blessures 11. Afin de réduire les risques d'électrocution, ne démontez pas l'appareil, mais apportez-le plutôt à un centre de service qualifié s'il doit être réparé. En enlevant le couvercle, vous vous exposez à des tensions dangereuses ou autres dangers similaires. Un remontage inadéquat peut être à l'origine d'une électrocution lors d'une utilisation ultérieure de l'appareil. Débranchez l'appareil avant de procéder au nettoyage. Utilisez un chiffon humide et doux.
  - 12. Ne surchargez pas les prises de courant et les
  - 13. Débranchez cet appareil de la prise de courant et communiquez avec le département de service à la clientèle de VTech dans les cas
  - Lorsque le cordon d'alimentation est endommagé ou écorché.
  - Si du liquide a été échappé dans l'appareil. • Si l'appareil a été exposé à une source d'humidité telle que la pluie ou l'eau.
  - Si le produit ne fonctionne pas normalement en respectant les instructions de fonctionnement. Réglez uniquement les commandes indiquées dans le les instructions de fonctionnement. Les réglages incorrects des autres commandes pourraient provoquer un dommage qui

pourrait exiger un travail exhaustif de la part

d'un technicien autorisé afin de rétablir le

- fonctionnement normal de l'appareil. Si le produit a été échappé et que le socle et/ou le combiné a été endommagé • Si le produit affiche une nette diminution de
- sa performance. 14. Évitez d'utiliser un téléphone (autre qu'un sans fil) pendant un orage. Les éclairs peuvent être
- 15. N'utilisez pas le téléphone pour rapporter une fuite de gaz à proximité de la fuite. En certaines circonstances, une flammèche pourrait être provoquée lorsque l'adaptateur

est branché à une prise de courant, ou lorsque le combiné est déposé sur le socle. Ceci est un événement commun associé à la fermeture d'un circuit électrique. L'utilisateur ne devrait pas brancher le téléphone à une prise de courant, et ne devrait pas déposer le combiné chargé sur le socle, si le téléphone se trouve à proximité d'un endroit comportant des concentrations de gaz inflammables, à moins que la ventilation soit adéquate. Une flammèche dans un tel endroit pourrait provoquer un incendie ou une explosion. De tels environnements peuvent comprendre: des endroits où l'on utilise de l'oxygène médical sans ventilation adéquate; des gaz industriels (dissolvants de nettoyage, des vapeurs d'essence, etc.); une fuite de gaz 16. Ne placez que le combiné de votre téléphone

- près de votre oreille lorsqu'en mode de
- 17. Ces adaptateurs ont été concus pour être orientés en position verticale ou montés au sol. Les broches ne sont pas conçues pour maintenir l'adaptateur en place si celui-ci est barnché dans une prise au plafond ou sous une table/ armoire 18. Pour le MATERIEL RACCORDE PAR PRISE DE
- COURANT, le socle de prise de courant doit etre installe a proximite du materiel et doit etre aisement accessible.
- 19. MISE EN GARDE: Il peut y avoir un risque d'explosion si vous utilisez le mauvais type de piles pour le téléphone. N'utilisez que les piles rechargeable inclus ou les piles de rechange (BT183342/BT283342). N'incinérez pas les piles. Celles-ci risqueraient d'exploser
- 20. N'utilisez que les adaptateurs inclus avec ce produit. L'utilisation d'un adaptateur dont la polarité ou la tension serait inadéquate risque d'endommager sérieusement le produit et mettre votre sécurité en péril. Adaptateur d'unité de base: Sortie: 6V CC 600 mA Adaptateur d'unité de charger: Sortie: 6V CC 400 mA

## **CONSERVEZ CES INSTRUCTIONS**

### About cordless telephones N'utilisez que la pile incluse ou l'équivalent.

Pour commander une pile de recharge, visitez

notre site Web au www.vtechphones.com

instructions spécifiques de mise aux rebus

Ne jetez pas la pile au feu. Vérifiez les

N'ouvrez pas et ne mutilez pas la pile.

auprès des autorités locales

par des matériaux conducteurs.

Stimulateurs cardiaques implantés dans

aux téléphones numériques sans fil) :

WTR recommande aux médecins

celui-ci est en marche

ce guide d'utilisation.

le 1-800-267-7377.

si avalé

l'organisme

cardiaque.

ou composez le 1-800-595-9511. Au Canada,

visitez le www.vtechcanada.com ou composez

L'électrolyte qui s'en échapperait est corrosif et

aux yeux ou à la peau. L'électrolyte est toxique

piles afin d'éviter les courts-circuits provoqués

selon les instructions et limites spécifiées dans

Les simulateurs cardiaques (s'applique uniquement

L'organisme 'Wireless Technology Research, LLC

interférences entre les téléphones sans fil portatifs

aliments et droques (FDA) des États-Unis, la firme

Avis aux détenteurs de stimulateurs cardiaques

Ils ne doivent PAS placer le téléphone sans

• Ils doivent utiliser le téléphone sans fil en

L'étude effectuée par l'organisme WRS n'a

pas identifié de risque pour les détenteurs de

simulateurs cardiaques causés par les gens qui

fil directement sur le stimulateur cardiaque,

tel que dans une poche de chemise, lorsque

l'appuyant sur l'oreille qui se trouve dans la

direction opposée au stimulateur cardiaque.

utilisent un téléphone sans fil à proximité de ceux-ci.

distance d'au moins six pouces du stimulateur

• Ils doivent tenir le téléphone sans fil à une

(WTR)', une firme de recherche indépendante,

a mené une évaluation pluridisciplinaire des

et les stimulateurs cardiaques implantés dans

l'organisme. Appuyée par l'Administration des

pourrait causer des brûlures ou des blessures

Soyez prudents lorsque vous manipulez les

Rechargez la pile incluse avec cet appareil,

telephone convenient create some limitations. Telephone calls are transmitted between the telephone base and the cordless handset by radio waves, so there is a possibility that the cordless telephone conversations could be intercepted by radio receiving equipment within range of the cordless handset. For this reason, you should not think of cordless telephone conversations as being as private as

those on corded telephones.

- **Electrical power:** The telephone base of this cordless telephone must be connected to a working electrical outlet. The electrical outlet should not be controlled by a wall switch. Calls cannot be made from the cordless handset if the telephone base is unplugged, switched off or if the electrical power is interrupted.
- Potential TV interference: Some cordless telephones operate at frequencies that may cause interference to televisions and VCRs. To minimize or prevent such interference, do not place the telephone base of the cordless telephone near or on top of a TV or VCR. If interference is experienced, moving the cordless telephone farther away from the TV or VCR often reduces or eliminates the interference.
- Rechargeable batteries: Exercise care in handling batteries in order not to create a short circuit with conducting material such as rings, bracelets and keys. The battery or conductor may overheat and cause harm. Observe proper polarity between the battery and the battery charge
- Nickel-metal hydride rechargeable batteries: Dispose of these batteries in a safe manner. Do not burn or puncture the battery. Like other batteries of this type, if burned or punctured, they could release caustic material which could cause injury.

### The RBRC® seal

• **Privacy:** The same features that make a cordless The RBRC® seal on the nickel-metal hydride battery indicates that VTech Communications, Inc. is voluntarily participating in an industry program to collect and recycle these batteries at the end of their useful lives, when taken out of service within the United States and Canada.

> The RBRC® program provides a convenient alternative to placing used nickel-metal hydride batteries into the trash or municipal waste, which may be illegal in your area.

VTech's participation in RBRC makes it easy for you to drop off the spent battery at local retailers participating in the RBRC® program or at authorized VTech product service centers. Please call 1 (800) 8 BATTERY® for information on Ni-MH battery recycling and disposal bans/restrictions in your area. VTech's involvement in this program is part of its commitment to protecting our environment and conserving natural resources.



RBRC° and 1 (800) 8 BATTERY° are registered trademarks of **Rechargeable Battery Recycling** Corporation.

## FCC, ACTA and IC regulations

### FCC Part 15

NOTE: This equipment has been tested and found to comply with the requirements for a Class B digital device under Part 15 of the Federal Communications Commission (FCC) rules. These requirements are intended to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: Reorient or relocate the receiving antenna.

- Increase the separation between the equipment
- and receiver Connect the equipment into an outlet on a circuit different from that to which the receiver

is connected

CAN ICES-3 (B)/NMB-3(B).

This equipment complies with Part 68 of the FCC rules and with technical requirements adopted by the Administrative Council for Terminal Attachments (ACTA). The label on the back or bottom of this equipment contains, among other things, a product identifier in the format US:AAAEQ##TXXXX. This identifier must be provided to your telephone service provider upon request. The plug and jack used to connect this equipment

to premises wiring and the telephone network must comply with applicable Part 68 rules and technical telephone cord and modular plug is provided with RJ11 jack should normally be used for connecting to a single line and an RJ14 jack for two lines. See the

determine how many devices you may connect to your telephone line and still have them ring when you are called. The REN for this product is 

encoded as the 6th and 7th characters following the US: in the product identifier (e.g., if ## is 03, the REN is 0.3). In most, but not all areas, the sum of all RENs should be five (5.0) or less. For more information, please contact your telephone service

This equipment must not be used with Party Lines. If you have specially wired alarm dialing equipment connected to your telephone line, ensure the connection of this equipment does not disable your alarm equipment. If you have questions about what will disable alarm equipment, consult your telephone service provider or a qualified installer

If this equipment is malfunctioning, it must be unplugged from the modular jack until the problem has been corrected. Repairs to this telephone equipment can only be made by the manufacturer or its authorized agents. For repair procedures, follow the instructions outlined under the **Limited warranty**.

If this equipment is causing harm to the telephone network, the telephone service provider may temporarily discontinue your telephone service. The telephone service provider is required to notify you before interrupting service. If advance notice is not practical, you will be notified as soon as possible. You will be given the opportunity to correct the problem and the telephone service to file a complaint with the FCC. Your telephone service provider may make changes in its facilities, equipment, operation, or procedures that could affect the proper functioning of this product. The telephone service provider is required to notify you if such changes are planned. If this product is equipped with a corded or

cordless handset, it is hearing aid compatible. If this product has memory dialing locations. you may choose to store emergency telephone numbers (e.g., police, fire, medical) in these locations. If you do store or test emergency numbers, please:

Remain on the line and briefly explain the reason for the call before hanging up. Perform such activities in off-peak hours, such as early morning or late evening.

# **Industry Canada**

This device complies with Industry Canada licenceexempt RSS standard(s)

Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Privacy of communications may not be ensured when using this telephone The term "IC:" before the certification/registration

For C-UL compliance only

Mesures de sécurité importantes

garde inscrites sur l'appareil.

votre téléphone :

la douche.

endommagé

corporelles ou d'électrocution, suivez toujours ces

mesures préventives de base lorsque vous utilisez

1. Lisez et comprenez bien toutes les instructions.

2. Observez toutes les instructions et mises en

3. Débranchez ce téléphone de la prise murale

nettoyeurs liquides ni en aérosol. N'utilisez

qu'un chiffon doux et légèrement humecté.

que près d'un bain, d'un lavabo, d'un évier

piscine, ou dans un sous-sol humide ou sous

de cuisine, d'un bac de lavage ou d'une

5. Ne déposez pas ce téléphone sur un chariot,

support ou table chancelants. L'appareil

pourrait tomber et être sérieusement

6. Évitez d'installer le système téléphonique

dans les endroits soumis à une température

électriques ou électroniques. Protégez votre

poussière, les vapeurs et les liquides corrosifs

téléphone contre les sources d'humidité, la

d'ouvertures d'aération situées à l'arrière ou

en dessous. Afin d'empêcher la surchauffe.

en placant l'appareil sur un lit, divan, tapis

ou autre surface similaires. Ne placez pas

cet appareil à proximité d'un élément de

chauffage ni d'une plinthe électrique. De

ou un cabinet fermé qui ne possède pas

8. Ne faites fonctionner cet appareil qu'avec le

de l'appareil. Si vous ne connaissez pas le

marchand ou votre fournisseur d'électricité.

voltage de votre maison, consultez votre

d'aération adéquate

plus, ne l'installez pas dans une unité murale

type d'alimentation indiqué sur les étiquettes

ces ouvertures ne doivent pas être obstruées

extrême, à la lumière directe du soleil ou

à proximité immédiate d'autres appareils

7. Le boîtier de l'appareil est doté de fentes et

avant de le nettoyer. N'utilisez pas de

4. N'utilisez pas ce produit près de l'eau, tel

number only signifies that the Industry Canada technical specifications were met. The Ringer Equivalence Number (REN) for this terminal equipment is 1.0. The REN indicates the maximum number of devices allowed to be connected to a telephone interface. The termination of an interface may consist of any

This product meets the applicable Innovation. Science and Economic Development Canada technical specifications.

combination of devices subject only to the

devices not exceed five.

requirement that the sum of the RENs of all the

## California Energy Commission battery charging testing

This telephone meets the California Energy Commission (CEC) regulations for energy consumption. It is not necessary to activate the energy conserving mode during normal usage, unless you want to charge the battery only and disable all telephone functions.

## To activate the CEC battery charging testing mode:

- 1. Unplug the telephone base power adapter from the power outlet. Make sure all handsets are plugged wit charged batteries before proceeding.
- 2. While you press and hold **PAGE**, plug the telephone base power adapter back to the power outlet. 3. After about 20 seconds, release **PAGE** and then press it
- again within 2 seconds. The process takes up to one minute to complete. When the phone successfully enters the CEC battery charging testing mode, all handsets display **To register, see user**

## ■ Note

• When the phone fails to enter this mode, repeat Step 1 through Step 3 above. The telephone base will be powered up as normal if you fail to press PAGE within 2 seconds in Step 3.

## To deactivate the CEC battery charging testing mode:

- 1. Unplug the telephone base power adapter from the power outlet, and then plug it back in. Then the telephone base is powered up as normal.
- 2. Place the handset in the telephone base to register it back. The handset displays **Registering...** Please wait.

## ☐ Note

The handset shows HANDSET X registered and you hear a beep when the registration process completes. The registration process takes about 90 seconds to complete

# Limited Warranty

## What does this limited warranty cover?

à l'origine d'une électrocution.

The manufacturer of this VTech Product warrants to the holder of a valid proof of purchase ("Consumer" or "you") that the Product and all accessories provided in the sales package ("Product") are free from defects in material and workmanship, pursuant to the following terms and conditions, when installed and used normally and in accordance with the Product operating instructions. This limited warranty extends only to the Consumer for Products purchased and used in the United States of America and Canada.

## What will VTech do if the Product is not free from defects in materials and workmanship during the limited warranty period ("Materially Defective

During the limited warranty period, VTech's authorized service representative will repair or replace at VTech's option, without charge, a Materially Defective Product. If we repair the Product, we may use new or refurbished replacement parts. If we choose to replace the Product, we may replace it with a new or refurbished Product of the same or similar design We will retain defective parts, modules, or equipment. Repair or replacement of the Product. at VTech's option, is your exclusive remedy. VTech will return the repaired or replacement Products to you in working condition. You should expect the repair or replacement to take approximately

## How long is the limited warranty period?

The limited warranty period for the Product extends for ONE (1) YEAR from the date of purchase. If VTech repairs or replaces a Materially Defective Product under the terms of this limited warranty, this limited warranty also applies to the repaired or replacement Product for a period of either (a) 90 days from the date the repaired or replacement Product is shipped to you or (b) the time remaining on the original one-year warranty; whichever is longer.

# What is not covered by this limited warranty?

This limited warranty does not cover:

Product that has been subjected to misuse, accident, shipping or other physical damage, improper installation, abnormal operation or handling, neglect, inundation, fire, water or other liquid intrusion; or 2. Product that has been damaged due to repair,

alteration or modification by anyone other

than an authorized service representative of

- Product to the extent that the problem experienced is caused by signal conditions, network reliability, or cable or antenna systems; or 4. Product to the extent that the problem is
- caused by use with non-VTech accessories; or. 5. Product whose warranty/quality stickers, product serial number plates or electronic serial numbers have been removed, altered or
- Product purchased, used, serviced, or shipped for repair from outside the United States of America or Canada, or used for commercial or institutional purposes (including but not limited to Products used for rental purposes);
- 7. Product returned without a valid proof of purchase (see item 2 on the next page); or
- 8. Charges for installation or set up, adjustment of customer controls, and installation or repair of systems outside the unit.

## How do you get warranty service?

rendered illegible; or

To obtain warranty service in the United States of America, please visit our website at www.vtechphones.com or call 1 (800) 595-9511. In Canada, go to **www.vtechcanada.com** or dial 1 (800) 267-7377.

user's manual - a check of the Product's controls and features may save you a service call. Except as provided by applicable law, you assume

the risk of loss or damage during transit and transportation and are responsible for delivery or handling charges incurred in the transport of the Product(s) to the service location. VTech will return repaired or replaced Product under this limited warranty. Transportation, delivery or handling charges are prepaid. VTech assumes no risk for damage or loss of the Product in transit. If the Product failure is not covered by this limited warranty, or proof of purchase does not meet the terms of this limited warranty. VTech will notify you and will request that you authorize the cost of repair prior to any further repair activity. You must pay for the cost of repair and return shipping costs for the repair of Products that are not covered by this limited warranty.

## What must you return with the Product to get warranty service?

- Return the entire original package and contents including the Product to the VTech service location along with a description of the malfunction or difficulty; and
- 2. Include a "valid proof of purchase" (sales receipt) identifying the Product purchased (Product model) and the date of purchase or
- Provide your name, complete and correct mailing address, and telephone number.

## Other limitations

This warranty is the complete and exclusive agreement between you and VTech. It supersede all other written or oral communications related to this Product. VTech provides no other warranties for this Product. The warranty exclusively describe all of VTech's responsibilities regarding the Product. There are no other express warranties. No one is authorized to make modifications to this limited warranty and you should not rely on any such modification.

State/Provincial Law Rights: This warranty gives you specific legal rights, and you may also have other rights, which vary from state to state or NOTE: Before calling for service, please review the province to province. Limitations: Implied warranties, including those of

> fitness for a particular purpose and merchantability (an unwritten warranty that the Product is fit for ordinary use) are limited to one year from the date of purchase. Some states/provinces do not allow limitations on how long an implied warranty lasts, so the above limitation may not apply to you. In no event shall VTech be liable for any indirect, special, incidental, consequential, or similar damages (including, but not limited to lost profits or revenue, inability to use the Product or other associated equipment, the cost of substitute equipment, and claims by third parties) resulting from the use of this Product. Some states/ provinces do not allow the exclusion or limitation of incidental or consequential damages, so the above limitation or exclusion may not apply to

Please retain your original sales receipt as proof of purchase.

## **Technical Specifications**

Frequency control	Crystal controlled PLL synthesizer
Transmit frequency	1921.536-1928.448 MHz
Channels	5
Nominal effective range	Maximum power allowed by FCC and IC. Actual operating range may vary according to environment conditions at the time of use.
Power requirements	Handset: 2.4V Ni-MH battery
	Charger: 6V DC @ 400mA
Memory	Phonebook: 50 memory locations; up to 30 digits and 15 characters
	Caller ID log: 50 memory locations; up to 24 digits and 15 characters
	Call block: 1000 entries

authority to operate the equipment This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Privacy of communications may not be ensured when using

WARNING: Changes or modifications to this

equipment not expressly approved by the party

responsible for compliance could void the user's

Consult the dealer or an experienced radio/TV

### **RF Radiation Exposure Statement**

this telephone.

technician for help.

To ensure safety of users, the FCC has established criteria for the amount of radio frequency energy that can be safely absorbed by a user or bystander according to the intended usage of the product. This product has been tested and found to comply with the FCC criteria. For body worn operation, this handset has been tested and meets the FCC RF exposure guidelines. Use of other accessories may not ensure compliance with FCC RF exposure guidelines. The handset may be safely held against the ear of the user. The telephone base shall be installed and used such that parts of the user's body other than the hands are maintained at a distance of approximately 20 cm (8 inches) or more. This Class B digital apparatus complies with Canadian requirement:

## FCC Part 68 and ACTA

requirements adopted by ACTA. A compliant this product. It is designed to be connected to a compatible modular iack that is also compliant. An installation instructions in the user's manual. The Ringer Equivalence Number (REN) is used to

Specifications are subject to change without notice © 2018 for VTech Communications, Inc. All rights reserved. 05/18. DS6250\_CIB\_V1.0 Document order number: 91-011441-010-100

