

# Quick start guide

for models DS6221/DS6221-2/DS6221-3/ DS6221-4/DS6221-5/DS6222-4/DS6222-5

### Install the telephone base and charger(s)

Install the telephone base and charger(s) as shown below.



- Use only the power adapter(s) and battery(ies) supplied with your VTech telephone.
  - For complete feature instructions, please refer to your user's manual.

### Battery installation and charging

Install the battery as shown below. After installing the battery, you might be able to make and receive short calls. For best performance, charge the handset battery for at least 16 hours before use.

# 2

1

3

(5)

If the batterv

Plug the battery compartment cover is on connector securely into the socket inside the handset, press the indentation and slide the the handset batterv compartment, matching cover to remove. the color-coded label.



Place the battery with the label THIS SIDE against the battery **UP** facing up and the wires inside the battery compartment.

compartment, then slide it towards the center of the handset until it clicks into place.



-4-5-6 7-3-9

000

Charge the handset by placing it in the telephone base or charger. The CHARGE light is on when vtech the handset charges.

**CHARGE** light

# Make, answer and end a call

### Make a call

1. Press tak or ■)). You hear a dial tone.

2. Dial the number.

### Predial a call

1. Dial the number. 2. Press the or ■).

### Answer a call

Press ( ) or any of the dialing keys (0-9, #, \*).

### End a call

Press OFF/CLEAR or put the handset in the telephone base or charger.



### Turn the answering system on or off

The answering system must be turned on to answer and record messages.

When the answering system is turned on, the ANS ON/OFF light on the telephone base will be on and ANS ON will display on the handset.

# To turn on or off with the telephone





### To turn on or off with a handset:

- 1. Press **MENU/SELECT** to show the menu when the handset is not in use.
- 2. Press MENU/SELECT to select >ANS. SYSTEM.
- 3. Press  $\blacktriangle$  or  $\checkmark$  to select >ANS SYS SETUP. then press MENU/SELECT.
- 4. Press MENU/SELECT to select >ANSWER ON/OFF.
- 5. Press  $\blacktriangle$  or  $\checkmark$  to choose **ON** or **OFF**, then press MENU/SELECT.

base:

### **Outgoing announcement**

The telephone is preset with a greeting that answers calls with *"Hello, please leave a message after the tone."* You can use this preset announcement, or replace it with your own.

## Use a handset to record your own announcement:

- 1. Press **MENU/SELECT** to show the menu when the handset is not in use.
- 2. Press MENU/SELECT to select >ANS. SYSTEM.
- 3. Press ▲ or ▼ to select >ANS SYS SETUP, then press MENU/SELECT.
- Press ▲ or ▼ to select >ANNOUNCEMENT, then press MENU/SELECT.
- 5. The handset announces, *"To play, press 2. To record, press 7."* Press **7** to record.
- 6. The handset announces, *"Record after the tone. Press 5 when you are done."*
- 7. After the tone, speak towards the microphone of the handset.
- 8. Press **5** when finished.
- The answering system automatically plays back the newly recorded announcement. Press 5 to stop the playback at anytime; 2 to replay the recorded announcement; or 7 to record again if desired; or 3 to delete your own recorded announcement.

# To play messages with the telephone base:

Press /=/PLAY/STOP to play messages and stop playback.

Options during playback:

- Press ▼ VOL ▲ to adjust the speaker volume.
- Press ►/SKIP to skip to the next message.
- Press **«/REPEAT** to repeat the message currently playing. Press **«/REPEAT** twice to listen to the previous message.
- Press X/DELETE to delete the current message.

#### To play messages with a handset:

- 1. Press **MENU/SELECT** to show the menu when the handset is not in use.
- 2. Press MENU/SELECT to select >ANS. SYSTEM.
- 3. Press MENU/SELECT to select >PLAY MSGS.

Options during playback:

- Press **▼ VOL ▲** to adjust the speaker volume.
- Press 6 to skip to the next message.
- Press 4 to repeat the message currently playing. Press 4 twice to listen to the previous message.
- Press 3 to delete the current message.
- Press 5 to stop.

### **IMPORTANT!**

If your product is not working properly:

- Refer to the **Troubleshooting** section of the user's manual.
- Visit our website at www.vtechphones.com or call 1 (800) 595-9511. In Canada, go to www.vtechcanada.com or dial 1 (800) 267-7377.