

Go to [www.vtechphones.com](http://www.vtechphones.com) to register your product for enhanced warranty support and latest VTech product news.

RM5854HD  
RM5854-2HD  
5-inch Smart Wi-Fi 1080p  
Video Monitor



For more support information



## vttech®

### Quick start guide

### Congratulations

on purchasing your new VTech product. Before using this HD video monitor, please read **Important safety instructions**.

For support, shopping, and everything new at VTech, visit our website at [www.vtechphones.com](http://www.vtechphones.com). In Canada, visit [www.vtechcanada.com](http://www.vtechcanada.com).

#### What does HD Video Monitor do?

VTech 5-inch Smart Wi-Fi 1080p Video Monitor allows you to stay close to your baby when you are on the move or away.

This monitor is Wi-Fi enabled, which uses your home wireless network to stream live video and audio through the HD baby unit and 5-inch color screen parent unit. It allows you to maintain a constant connection to your baby.

You can also monitor from your smartphone and mobile tablet.

VTech 5-inch Smart Wi-Fi 1080p Video Monitor uses **MyVTech Baby Pro** app to let you instantly see and hear what's happening with your baby from anywhere in the world.

The app can be downloaded from the App Store or the Google Play™ Store, directly from your smartphone or mobile tablet.

## IMPORTANT SAFETY INSTRUCTIONS

The applied nameplate is located at the bottom of the baby unit's base.

When using your equipment, basic safety precautions should always be followed to reduce the risk of fire, electric shock and injury, including the following:

1. Follow all warnings and instructions marked on the product.
2. Adult setup is required.
3. **CAUTION:** Do not install the baby unit at a height above 2 meters.
4. This product is intended as an aid. It is not a substitute for responsible and proper adult supervision and should not be used as such.
5. This product is not intended for use as a medical monitor.
6. Do not use this product near water. For example, do not use it next to a bath tub, wash bowl, kitchen sink, laundry tub or swimming pool, or in a wet basement or shower.
7. **CAUTION:** Use only the battery provided. There may be a risk of explosion if a wrong type of battery is used for the parent unit. The battery cannot be subjected to high or low extreme temperature and low air pressure at high altitude during use, storage or transportation. Disposal of battery into fire or a hot oven, or mechanically crushing or cutting the battery can result in an explosion. Leaving the battery in an extremely high temperature surrounding environment can result in an explosion or the leakage of flammable liquid or gas. Battery subjected to extremely low air pressure may result in an explosion or the leakage of flammable liquid or gas. Dispose of used battery according to the information in **The RBRC seal**.
8. Use only the adapters included with this product. Incorrect adapter polarity or voltage can seriously damage the product.

**Power adapter information:**  
Output: 5V DC 1000mA  
VTECH Telecommunications Ltd.  
Model: VT05EUS05100

**Rechargeable battery information:**  
3.8V 2100mAh Lithium-ion battery  
Zhongshan Tianmao battery Co. Ltd.  
Model: BP1763

The power adapter is intended to be correctly oriented in a vertical or floor mount position. The prongs are designed to hold the plug in place if it is plugged into a ceiling, under-table or cabinet outlet.

For pluggable equipment, the socket-outlet (power adapter) shall be installed near the equipment and shall be easily accessible.

Unplug this product from the wall outlet before cleaning. Do not use liquid or aerosol cleaners. Use a damp cloth for cleaning.

Do not cut off the power adapters to replace them with other plugs, as this causes a hazardous situation.

Do not allow anything to rest on the power cords. Do not install this product where the cords may be walked on or crimped.

This product should be operated only from the type of power source indicated on the marking label. If you are not sure of the type of power supply in your home, consult your dealer or local power company.

The equipment is to be supplied from an identified USB port complying with the requirements of Limited Power Source. Do not overload wall outlets or use an extension cord.

Do not place this product on an unstable table, shelf, stand or other unstable surfaces.

This product should not be placed in any area where proper ventilation is not provided. Slots and openings in the back or bottom of this product are provided for ventilation. To protect them from overheating, these openings must not be blocked by placing the product on a soft surface such as a bed, sofa or rug. This product should never be placed near or over a radiator or heat register.

Never push objects of any kind into this product through

the slots because they may touch dangerous voltage points or create a short circuit. Never spill liquid of any kind on the product.

20. To reduce the risk of electric shock, do not disassemble this product, but take it to an authorized service facility. Opening or removing parts of the product other than specified access doors may expose you to dangerous voltages or other risks. Incorrect reassembling can cause electric shock when the product is subsequently used.
21. You should test the sound reception every time you turn on the units or move one of the components.
22. Periodically examine all components for damage.
23. There is a very low risk of privacy loss when using certain electronic devices, such as baby monitors, cordless telephones, etc. To protect your privacy, make sure the product has never been used before purchase, reset the baby monitor periodically by powering off and then powering on the units, and power off the baby monitor if you will not use it for some time.
24. Children should be supervised to ensure that they do not play with the product.
25. The small parts of this monitor can be swallowed by babies or small children. Keep these parts out of reach of children.
26. The product is not intended for use by persons (including children) with reduced physical, sensory or mental capabilities, or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the appliance by a person responsible for their safety.

#### SAVE THESE INSTRUCTIONS

**Cautions**

- Use and store the product at a temperature between 32°F and 104°F.
- Burn hazard, fire hazard, explosion hazard associated with mishandling of the battery.
- Do not expose the product to extreme cold, heat or direct sunlight. Do not put the product close to a heating source.

**Warning—Strangulation Hazard—Children have STRANGLED in cards. Keep this cord out of the reach of children (more than 3 ft (0.9m) away). Do not remove this tag.**

Never place the camera unit(s) inside the baby's crib or playpen. Never cover the camera unit(s) or parent unit with anything such as a towel or a blanket.

Other electronic products may cause interference with your camera unit. Try installing your camera unit as far away from these electronic devices as possible: wireless routers, radios, cellular telephones, intercoms, room monitors, televisions, personal computers, kitchen appliances and cordless telephones.

**Precutions for users of implanted cardiac pacemakers**

Cardiac pacemakers (applies only to digital cordless devices): Wireless Technology Research, LLC (WTR), an independent research entity, led a multidisciplinary evaluation of the interference between portable wireless devices and implanted cardiac pacemakers. Supported by the U.S. Food and Drug Administration, WTR recommends to physicians that:

**Pacemaker patients**

- Should keep wireless devices at least six inches from the pacemaker.
- Should NOT place wireless devices directly over the pacemaker, such as in a breast pocket, when it is turned ON.



WTR's evaluation did not identify any risk to bystanders with pacemakers from other persons using wireless devices.

**Electromagnetic fields (EMF)**

This VTech product complies with all standards regarding electromagnetic fields (EMF). If handled properly and according to the instructions in this user's manual, the product is safe to be used based on scientific evidence available today.

## WHAT'S IN THE BOX

Your HD video monitor package contains the following items. Save your sales receipt and original packaging in the event warranty service is necessary.



1 set for RM5854HD  
2 sets for RM5854-2HD




#### Requirements

##### For mobile access:


Network	Wi-Fi
Wi-Fi router	2.4GHz 802.11 b/g/n
Internet connection	1.5 Mbps @ 720p or 2.5 Mbps @1080p upload bandwidth per baby unit

## OVERVIEW

### Baby unit overview



### Parent unit overview



#### 1 Light sensor

#### 2 Camera lens

#### 3 Microphone

#### 4 Infrared LEDs

- Allow you to see clearly in a dark surrounding.

#### 5 Speaker

#### 6 Night light

- Press to turn the night light on or off.

#### 7 LED indicator

- Orange is steady on when the baby unit is connecting to the parent unit in direct mode.

- Green is steady on when the baby unit and parent unit are connecting to your home Wi-Fi network via the Wi-Fi router.

- Flashes orange slowly during video streaming in direct mode.

- Flashes green slowly during video streaming via home Wi-Fi network.

#### 8 ON

- Power on/off switch.

#### 9 PAIR

- Press and hold for three seconds to enter pairing mode.

- Reset the baby unit to factory default.

- 1. Press and hold **PAIR** key until you hear a beep sound.

- 2. Release the **PAIR** key, and then press the **PAIR** key again five times until you hear another beep sound.

- 3. The baby unit will sound another beep when the reset completes. Then, the baby unit will reboot.

#### 10 Night light


#### 11 Temperature sensor

#### 12 Slots for wall mounting

- Wall mount bracket is included in your package.

#### 13 Power jack

### Parent unit overview



#### 1 LINK LED light

- On when the parent unit is linked to the baby unit.

- Flashes when the link to the baby unit is lost.

#### 2 LED light

- On when the parent unit is connected to AC power, and the battery is charging.

- Off when the parent unit is disconnected from AC power.

- Flashes when the parent unit battery is low and needs charging.

#### 3 3-level sound indicator light

- Green on when low sound level is detected by the baby unit.

- Green and amber on when moderate sound level is detected by the baby unit.

- Green, amber and red on when high sound level is detected by the baby unit.

#### 4 TALK /

- Press and hold to talk to the baby unit.

- While in a submenu, press to exit.

#### 5


- Press to zoom in/out.

- While in a submenu, press to view the help menu.

## HOW THE SYSTEM WORKS

### Direct mode

The parent unit and the baby unit of your video monitor connect to each others in **Direct mode** by default, which allows you to stream live video right out of the box. **Direct mode** connection lets you stream live video from parent unit only.



#### Tip

- You may experience reduced signal strength if your parent unit and baby unit are far apart, or there are obstructing factors, such as internal walls, between them. Move the parent unit closer to the baby unit to improve the signal strength. You can also set up **Router mode** to connect via your home Wi-Fi network to improve the connection between your parent unit and baby unit.

### Router mode

You can continue using your video monitor with **Direct mode** connection, or you can set up your monitor in **Router mode** connection.

**Router mode** uses your home Wi-Fi network to connect your video monitor. It supports streaming live video through parent unit and smartphone app.

We recommend that you set up your monitor in **Router mode** to enjoy streaming live video via your parent unit with better connection.

If you want to stream live video remotely with your mobile device, download and install the **MyVTech Baby Pro** mobile app. With the mobile app, your Wi-Fi router (not included) provides Internet connectivity to your HD video monitor system. It serves as a communicating channel between your baby unit and mobile device, allowing you to monitor and/or control your baby unit wherever you are. For detail, see **Download app for mobile access** section in this quick start guide.

#### NOTES

- Your parent unit detects the connection signal strength. If you have connected your video monitor with your home Wi-Fi network, your parent unit automatically switches to direct or router mode - the one that has stronger signal strength.
- When both parent unit and app are viewing the camera simultaneously, the video quality will be optimised to deliver the best possible viewing result.

All rights reserved. 04/21 RM5854-KHD, OSO, V1  
Specifications are subject to change without notice.



iOS is a trademark or registered trademark of Cisco in the U.S. and other countries and is used under license.  
App Store is a trademark of Apple Inc., registered in the U.S. and other countries.  
Android™ and Google Play™ are trademarks of Google Inc.



Phone: 1 (800) 595-9511 in the U.S. or 1 (800) 267-7377 in Canada  
Address: 9020 SW Washington Square Road - 555 Tigard, OR 97223, United States  
Company: VTech Telecommunications, Inc.  
VTECH, VT05EUS05100  
Rated output: 5V DC, 1000mA.  
Parent unit/Baby unit power adapters:  
VTECH, VT05EUS05100

VTech Telecommunications, Inc. and its suppliers assume no responsibility for any damage or loss resulting from the use of this user's manual. VTech Telecommunications, Inc. and its suppliers assume no responsibility for any loss or claims by third parties that may arise through the use of this product.

## DISCLAIMER AND LIMITATION OF LIABILITY

Frequency	Baby unit: 2412 - 2442 MHz
Channels	11
LCD	5" Color LCD
Normal effective range	Maximum power allowed by FCC and IC. Actual operating range may vary according to environmental conditions at the time of use. (FIS 1280X720 pixels)
Power requirement	Parent unit/Baby unit power adapters: VTECH, VT05EUS05100 Rated output: 5V DC, 1000mA. Parent unit battery: BP1763 (3.8V 2100mAh Lithium-ion battery)

## TECHNICAL SPECIFICATIONS



